

The brand new GoodWe ET Series is a three-phase high voltage energy storage inverter that enables enhanced energy independence and maximizes self-consumption through export limit feature and time of use shifts for reduced electric bills. Covering a power range of 5 kW, 8 kW and 10 kW, the ET Series allows up to 100% oversizing to maximize power output and features Uninterruptible Power Supply (UPS) to inductive loads such as air conditioners or refrigerators with an automatic switchover time of less than 10 milliseconds, providing grid-tied savings when the grid is up and off-grid independence and security when it is down or compromised.



Uninterruptible Power Supply



Maximum Efficiency up to 98.3%



Compact Size & Light Weight



Fanless Design, Quiet Operation



Wide Battery Voltage Range

chnical Data	GW5K-ET	GW8K-ET	GW10K-ET
Battery Type Battery Voltage Range (V) Max. Charging Current (A) Max. Discharging Current (A) Charging Strategy for Li-lon Battery Charging Strategy for Lead-acid Battery(Reserved)	Li-lon 180~550 25 25 Self-adaption to BMS 3-stage adaptive with maintenance	Li-lon 180~550 25 25 Self-adaption to BMS 3-stage adaptive with maintenance	Li-lon 180~550 25 25 Self-adaption to BMS 3-stage adaptive with maintenance
Max. DC Input Power (W) Max. DC Input Voltage (V) MPPT Range (V) Start-up Voltage (V) MPPT Range for Full Load (V) Nominal DC Input Voltage (V) Max. Input Current (A) Max. Short Current (A) No. of MPP Trackers No. of Strings per MPP Tracker	6500 1000 200~850 180 240~850 620 11/11 13.8/13.8 2 1/1	9600 1000 200~850 180 380~850 620 11/11 13.8/13.8 2	13000 1000 200~850 180 460~850 620 11/11 13.8/13.8 2 1/1
Nominal Apparent Power Output to Utility Grid (VA) Max. Apparent Power Output to Utility Grid (VA)* Max. Apparent Power from Utility Grid (VA) Nominal Output Voltage (V) Nominal Ouput Freqency (Hz) Max. AC Current Output to Utility Grid (A) Max. AC Current From Utility Grid (A) Output Power Factor Output THDi (@Nominal Output)	5000 5000 10000 400/380, 3L/N/PE 50/60 8.5 15.2 ~1	8000 8000 15000 400/380, 3L/N/PE 50/60 13.5 22.7 (Adjustable from 0.8 leading to 0.8 laggi	10000 11000 * 15000 400/380, 3L/N/PE 50/60 16.5 22.7 ing)
Max. Output Apparent Power (VA)** Peak Output Apparent Power (VA)** Max. Ouput Current (A) Nominal Output Voltage (V) Nominal Ouput Frequency (Hz) Output THDv (@Linear Load)	5000 10000, 60sec 8.5 400/380 50/60 <3%	8000 16500, 60sec 13.5 400/380 50/60 <3%	10000 16500, 60sec 16.5 400/380 50/60 <3%
Max. Efficiency Max. Battery to Load Efficiency Euro Efficiency	98.0% 97.5% 97.0%	98.3% 97.5% 97.0%	98.3% 97.5% 97.0%
Anti-islanding Protection PV String Input Reverse Polarity Protection Insulation Resistor Detection Residual Current Monitoring Unit Output Over Current Protection Output Short Protection Battery Input Reverse Polarity Protection Output Over Voltage Protection	Integrated	Integrated Integrated Integrated Integrated Integrated Integrated Integrated Integrated Integrated	Integrated Integrated Integrated Integrated Integrated Integrated Integrated Integrated Integrated
Operating Temperature Range (°C) Relative Humidity Operating Altitude (m) Cooling Noise (dB) User Interface Communication with BMS Communication with Meter Communication with EMS Communication with Portal Weight (kg) Size (Width*Height*Depth mm) Mounting Protection Degree	-35~60 0~95% ≤4000  Nature Convection <30  LED & APP R5485; CAN R5485 RS485 (Insulated) Wi-Fi 25 415*516*160 Wall Bracket IP65	-35~60 0~95% ≤4000  Nature Convection <30  LED & APP R5485; CAN R5485 RS485 (Insulated) Wi-Fi 25 415*516*160 Wall Bracket IP65	-35~60 0~95% ≤4000  Nature Convection <30  LED & APP R5485; CAN R5485 RS485 (Insulated) Wi-Fi 25 415*516*160  Wall Bracket IP65
	Battery Voltage Range (V) Max. Charging Current (A) Max. Discharging Current (A) Charging Strategy for Li-Ion Battery Charging Strategy for Lead-acid Battery(Reserved)  Max. DC Input Power (W) Max. DC Input Power (W) MPPT Range (V) Start-up Voltage (V) MPPT Range for Full Load (V) Nominal DC Input Voltage (V) MAX. Input Current (A) Max. Short Current (A) No. of MPP Trackers No. of Strings per MPP Tracker  Nominal Apparent Power Output to Utility Grid (VA) Max. Apparent Power Output to Utility Grid (VA) Max. Apparent Power from Utility Grid (VA) Nominal Output Voltage (V) Nominal Output Freqency (Hz) Max. AC Current Gutput to Utility Grid (A) Output Power Factor Output THDi (@Nominal Output)  Max. Output Apparent Power (VA)** Peak Output Apparent Power (VA)** Max. Output Apparent Power (VA)** Max. Output Voltage (V) Nominal Output Voltage (V) Nominal Output Voltage (V) Nominal Output Voltage (V) Nominal Output Frequency (Hz) Output THDv (@Linear Load)  Max. Efficiency Max. Battery to Load Efficiency Euro Efficiency Euro Efficiency Anti-islanding Protection PV String Input Reverse Polarity Protection Insulation Resistor Detection Residual Current Monitoring Unit Output Over Voltage Protection Output Short Protection Battery Input Reverse Polarity Protection Output Short Protection Output Over Voltage Protection Operating Temperature Range (°C) Relative Humidity Operating Altitude (m) Cooling Noise (dB) User Interface Communication with BMS Communication with Portal Weight (kg) Size (Width*Height*Depth mm) Mounting	Battery Voltage Range (V)         180–550           Max. Charging Current (A)         25           Max. Diskrapging Current (A)         25           Charging Strategy for Li-lon Battery         Self-adaption to BMS           Charging Strategy for Lead-acid Battery(Reserved)         3-stage adaptive with maintenance           Max. DC Input Power (W)         1000           Max. DC Input Voltage (V)         1000           MPPT Range for Full Load (V)         240–850           Start-up Voltage (V)         620           Max. Input Current (A)         11/11           Max. Input Current (A)         11/11           Max. Short Current (A)         13.8/13.8           No. of Strings per MPPTracker         1/1           No. of Strings per MPPTracker         1/1           Nominal Apparent Power Output to Utility Grid (VA)         5000           Max. Apparent Power form Utility Grid (VA)         5000           Max. Apparent Power from Utility Grid (VA)         10000           Nominal Output Frequency (Hz)         50/60           Max. AC Current Output to Utility Grid (A)         8.5           Max. Current From Utility Grid (A)         8.5           Max. Output Apparent Power (VA)**         5000           Peak Output Apparent Power (VA)**         5000 <tr< td=""><td>  Battery   Voltage Range (V)</td></tr<>	Battery   Voltage Range (V)

IEC62109-1&2, IEC62040-1 EN61000-6-1, EN61000-6-2, EN61000-6-3, EN61000-6-4, EN61000-4-16, EN61000-4-18, EN61000-4-29

Safety Regulation

<sup>\*:</sup> According to local grid regulation.

\*\*: Can be reached only if PV and battery power is enough.

\*\*\*: No Back-up output.